# Omega Cordless ESD Vacuum

by Atrix®











## **WARRANTY**

1 Year Limited

## CONVENIENT

Cordless and quiet (67 dB) with its 22 Volt DC Brushless Digital Motor and full-filter indicator light

## **POWERFUL**

As strong as the corded version with its 190-Watt cleaning power

#### **SAFE**


ESD Safe hose, utensils and ground cord to safely drain damaging static voltages to ground

## **APPLICATIONS**

Servicing and cleaning static sensitive equipment, i.e. computers, copiers, printers, data centers, ATM's, gaming, banking, robotics, telecomm and other areas where electrical outlets are scarce or where corded vacuums are cumbersome, time consuming or a safety hazard







## Omega Cordless ESD Vacuum by Atrix®

### **SPECIFICATIONS**

#### VACO22VESD

#### **DIMENSIONS**

Length: 20" (508 mm) Width: 6.25" (159 mm) Height: 9.25" (235 mm)

**WEIGHT** 11.20 lbs. (5.08 kg)

#### **HOSE DIAMETER**

Inside - 1.00" (25.4 mm) Outside - 1.25" (31.75 mm)

## **POWER**

22V, 190W

#### **CFM**

40 CFM

#### **FILTRATION**

**Immediate Containment UltraFine** 88% Efficient at .3 Micron 1 Gallon Dry **43 Pleat Cellulose** 

#### GENERAL INFORMATION

#### **PACKAGING**

Dimensions: L Inches: 20.25 7.75 12.55 mm: 514 197 318 Weight: 13.0 lbs. 5.9 kg

**HS Code** 8508.11.0000

**UPC** 

8 38067 00368 5

#### **OPTIONAL ACCESSORIES**

22 Volt Battery - VACOBAT



**ESD Safe HEPA** Filter Cartridge - OF912HE



**ESD Safe Fine Filtration Filter** Cartridge - 31800-1P



### **INCLUDED CONTENTS**

- A Omega Cordless ESD Vac by Atrix
- B VACOBAT- 22 Volt Battery, 30+ minute run time
- C VACOCHG- Charger 1 hr. w/3 Cords: USA, Euro, UK
- D 31700C- Immediate Containment Fine Filtration Filter Cartridge
- E 31654- ESD Safe Crevice Tool
- F 31657- ESD Safe Flexible Gooseneck Tool
- G 31671STUD- ESD Safe 10' Stretch Hose w/10MM Male Stud
- H 510-001-006- ESD Ground Cord w/10MM Female Stud and Alligator Clip

I - 410017- Disposable Filter Plug

- J AVPA005- Hose End Plug (2)
- K AVPA016- Adjustable Shoulder Strap

L - Permanently Attached Heavy Duty Filter Plug

